

CHANNEL	VALUE	FUNCTION
CH 1 MODE	000-063	Laser Block Out
	064-127	AUTO SHOW
	128-191	SOUND ACTIVATED SHOW (MUSIC)
	192-255	DMX MODE (Other channels activated)
CH 2	000-255	32 Patterns as shown in PATTERN LIST
CH 3 ZOOMING	0-127	100%-5% Size
	128-169	Zooming In
	170-209	Zooming Out
	210-255	Zooming In & Out
CH 4 Y AXIS ROLLING	000-127	0 -359 degree fixed Y axis rolled
	128-191	Clockwise rolling
	192-255	Anticlockwise rolling
CH 5 X AXIS ROLLING	000-127	0 -359 degree fixed X axis rolled
	128-191	Clockwise rolling
	192-255	Anticlockwise rolling
CH 6 Z AXIS ROTATING	000-127	0 -359 degree fixed Z axis rotate
	128-191	Clockwise rotating
	128-255	Anticlockwise rotating
CH 7 X AXIS MOVING	000-127	128 different fixed position on X
	128-191	Clockwise moving
	128-255	Anticlockwise moving
CH 8 Y AXIS	000-127	128 different fixed position on Y
	128-191	Clockwise moving