

This is powerful series of DMX LED COLOR BAR which with 27pcs of high power 1W RGB LED as lamp sources. It can run with dip switches for built-in programs, sound active function, master / slave mode and DMX control with different many control modes.

LED COLOR BAR 1W/27 is the best applications as color washer for setting the stage background, disco club, bar, building wall color or even for home using.

Dip 10 to ON and the other dipswitches to OFF as the slave unit's setting. Then these linked slave units will run following the master unit.

Dip 9 & Dip10 OFF, use Dip 1-Dip 4 to select different built-in running programs, the speed is adjustable by Dip 5 & Dip 6.

Set Dip 9 to ON for sound control function, the sound sensitivity can be adjusted by Dip 1, Dip 2, Dip 3 and Dip 4.

Set Dip 10 to ON, use Dip 1-9 as the DMX address setting to insert the DMX function as below chart:

[illegible]